

A-FRAME FAULT LOCATOR

RIDGID



The RIDGID® A-Frame Fault Locator is a purpose built system to simplify the location of ground faults in direct buried insulated wire.

- Purpose-built directional fault finder
- Locates insulation faults up to 2 megohms
- Reference readout to determine fault location
- Durable, lightweight powder-coated aluminum frame
- Weather proof membrane buttons



For more details visit
RIDGID.com/warranty

SPECIFICATIONS

FT-103 Transmitter:

| | |
|-----------------------------|--|
| Operating Frequencies..... | Direct Fault Finding: 797 Hz - "dFF" displayed Path locating: 128 Hz, 1 kHz, 8 kHz, 33kHz, 93 kHz Direct Connect: 128 Hz, 1 kHz, 8 kHz, 33kHz, 93 kHz Inductive Clamp: 8 kHz, 33 kHz, 93 kHz Broadcast Inductive: 33 kHz, 93 kHz |
| Load Range..... | 5 Ω to 2M Ω |
| Output Power..... | Up to 3 Watts (Low, medium and high settings) |
| Output Voltage..... | 5 Volts - 600 Volts |
| Power Supply..... | 8 × C-Cell Batteries (Included) |
| Dimensions (L × W × H)..... | 21.6 cm × 14.7 cm × 6,4 cm/8.5" × 5.8" × 2.5" |

FR-30 A-Frame Receiver:

| | |
|-----------------------------|--|
| Fault Finding Depth..... | Up up to 6 m (20') (depending on conditions) |
| Fault Finding Length..... | Up to 4.8 km (3 miles) (depending on conditions) |
| Display..... | Black and White LCD |
| Power Supply..... | 6 × AA Batteries (Included) |
| Dimensions (L × W × H)..... | 77.0 cm × 77.2 cm × 3.8 cm/30.3" × 30.4" × 1.5" |



ORDER INFORMATION

| CATALOG NO. | DESCRIPTION | WEIGHT | |
|--------------------------|---|--------|-----|
| | | Kg | Lb |
| 56613 | A-Frame Receiver (FR-30) and Transmitter (FT-103) | 2.3 | 5.2 |
| ACCESSORIES | | | |
| 20973 | SeekTech 4" Inductive Signal Clamp | 0.9 | 2.0 |
| 30123 | SeekTech SR-60 Line Locator | 2.3 | 5.1 |
| 46393 | SR-24 Line Locator with Bluetooth® and GPS | 1.8 | 4.0 |
| 21943 | SeekTech SR-20 Line Locator | 1.8 | 4.0 |
| REPLACEMENT PARTS | | | |
| 57753 | Transmitter, FT-103 3-Watt | 1.0 | 2.2 |
| 57758 | A-Frame Receiver, FR-30 Fault Locator | 1.3 | 3.0 |
| 57763 | Ground stake, FT-103 | .09 | 0.2 |
| 57768 | Red and black test leads, FT-103 | .09 | 0.2 |

Standard Equipment


- FR-30 A-Frame Receiver
- FT-103 Transmitter
- Ground stake
- Red and black test leads
- Carry cases
- Batteries
- Operator's Manual Pack



**Inductive Clamp
20973 (Sold separately)**



**SR-24 Utility Locator
46393 (Sold separately)**



RIDGID® reserves the right to change design and specification of our products without notification or alteration of literature. For the complete selection of the Ridgid Tool product line, please refer to the RIDGID® Tool Catalog or RIDGID.com.

© 2017, RIDGID, Inc. The Emerson logo and RIDGID logo are registered trademarks of Emerson Electric Co. or RIDGID, Inc. in the U.S. and other countries. All other trademarks belong to their respective holders.

DISTRIBUTOR



Ridge Tool Europe N.V.
IZ Schurhovenveld 4820
3800 Sint-Truiden, Belgium

Tel.: +32 (0)11 598 620
ridgid.eu@emerson.com
RIDGID.com

